

Heka  
LED 131Heka  
LED Kit**Technical Data**

Name & No.	Diagram	Wattage	kg	Description
Heka LED 131	O-	8W	0,70	<ul style="list-style-type: none"> <li>• IP 56</li> <li>• standard light with one integrated High Voltage/Mid Power LED module and specially developed globe of polycarbonate</li> <li>• brass casing, clear polycarbonate structured globe</li> <li>• cable gland: M24 x 1.5</li> <li>• voltage: 230V, 115V or 24V DC</li> <li>• luminous flux: approx. 800 lm (comparison: bulb 60W approx. 700 lm)</li> <li>• beam angle: 120°</li> <li>• high colour rendering index of 85 CRI</li> <li>• also available as a change kit for backfitting the existing lamps without demounting</li> </ul>
Heka LED 131/2	O=		0,80	
Heka LED 131/D	-O-		0,80	
Heka LED Kit		8W	0,22	<ul style="list-style-type: none"> <li>• change kit from Heka 131 to Heka LED 131: exchange in used lights without changing possible</li> <li>• voltage: 230V, 115V or 24V DC</li> <li>• consisting of: one High Voltage/Mid Power LED module, structured globe and mounting material</li> </ul>
				Your Advantages:
				<ul style="list-style-type: none"> <li>• no power supply necessary</li> <li>• low heat development</li> <li>• better optical light output ratio against lights with 60W bulbs</li> <li>• exchange with existing lamps without changes: same mounting points and measurements with conventionally Heka 131</li> <li>• long durability of LED</li> <li>• space-saving</li> </ul>

**Spare Parts**

No.	Description
1200434	LED application 115V
1200415	LED application 230V
1200734	clear structured globe
1213113	Heka change kit LED 115V
1213114	Heka change kit LED 230V

Polished products available for an extra charge.

Also available with red or green globe, supplement charge.